

EN Quick Setup Guide Mobile Setup



Extender N3



Extender N3A

1 Repeater mode

Plug in your wifi extender and wait for 30s

*Normal:

Plug in the power,
wait 1 minute,
the "WiFi" light turns green
and go to the next step




Abnormal:

Press "reset" hole on the bottom
of the product for 8s with a paperclip

4

Enter the default password: **admin**



7


Set your Extender SSID and password



10

The led light "Extender" will light up, that
means it Extender Mode successfully.

*NOTE:



2

Connect your extender SSID

Please connect to the
SSID of "wifi-XXXX".

*NOTE:


You can not surf the Internet until
you finish all the setting steps,
pls continue

"XXXX" is the last 4 digits letters
of MAC Address which appears
at the back of each product.




5

Scan and select your host router SSID



8

Check again and confirm the wireless Info




*NOTE:

After check,
click "Start Connect"
and wait 30-60s

11

Reselect and reconnect to your extender wifi



Reconnect the extender SSID,
then get access to Internet

3

Open your browser webpage
(Google&Firefox Browser Recommended)

*NOTE:

Pls make sure that you have
connected
the SSID(wifi-XXXX) of the
wifi extender successfully, most of
the PC/Mobile will recognize and
Sign in to the management page
automatically.
If not, pls enter 192.168.188.1
on the new browser.



6

Enter the password of your host router

*NOTE:

Pls make sure of the right
password (special characters
not allowed, like "%")



9

Wait for the repeater to connect to the router
successfully.


After the setting is completed, please observe the signal indicator. If it lights up, it means that the relay
is successful. Please connect AirLive-2.4-pro to the Internet!
otherwise reconnect.

Please wait 47 seconds

AP mode


If you need AP mode, please do RESET
then follow STEP 1 to STEP 4

Click [AP Settings]




Set Wireless Password

Click [Auth Mode] ---- select the encryption method,
generally select (WPA2PSK/WPA2PSK/AES)
to finish wireless password setting. Click [Apply]



Plug the Ethernet cable to the LAN port
directly then you can access the internet.



EN

Quick Setup Guide PC Setup



Extender N3



Extender N3A

Declaration of Conformity

We, Manufacturer/Importer
AirLive Technology Corporation
4F, No.132, Lane 235, Baoqian Rd., Xindian Dist.,
New Taipei City 23145, Taiwan

Declare that the product
2.4Ghz N300 Wireless Extender
Extender N3, N3A

is in conformity with
In accordance with 2014/53/EU Directive
Clause

- EN 55032:2015+A11:2020+A12020
- EN 55035:2017+A11:2020
- EN 61000-3-3:2013+A1:2019
- ETSI EN 301 489-1 V2.2.3 (2019-11)
- ETSI EN 301 489-17 V3.2.4 (2020-09)
- (LVD)
- EN IEC 62368-1:2020+A11:2020
- (Health)
- EN IEC 62311:2020
- (Radio)
- ETSI EN300 328 V2.2.2 (2019-07)

■ CE marking



Manufacturer/Importer

Name : A van Rossem Position/ Title : Product Manager
Place : Taiwan Date : October 2023

Conformity with

In accordance with RoHS 2.0 Directive (EU) 2015/863 and (EU) 2017/2102
Amending Annex II to Directive 2011/65/EU.

- IEC 62321-1:2013, IEC 62321-2:2013
- IEC 62321-3-1:2013, IEC 62321-3-2:2013
- IEC 62321-4:2013+A1:2017, IEC 62321-5:2013
- IEC 62321-6:2015, IEC 62321-7-1:2015
- IEC 62321-7-2:2017, IEC 62321-8:2017

www.airlive.com



CE AirLive Technology Corporation declares that this device is in compliance with the essential requirements of Radio Equipment Directive (RED) 2014/53/EU

1

Repeater mode

Plug in your wifi extender and wait for 30s

*Normal:

Plug in the power,
wait 1 minute,
the "WiFi" light turns green
and go to the next step



Abnormal:

Press "reset" hole on the bottom
of the product for 8s with a paperclip

2

Connect your extender SSID

Please connect to the
SSID of "wifi-XXXX".

*NOTE:

You can not surf the Internet until
you finish all the setting steps,
pls continue

"XXXX" is the last 4 digits letters
of MAC Address which appears
at the back of each product.




3

Open your browser webpage
(Google/Firefox Browser Recommended)


*NOTE:

Pls make sure that you have
connected
the SSID(wifi-XXXX) of the
wifi extender successfully, most of
the PC/Mobile will recognize and
Sign in to the management page
automatically.
If not, pls enter 192.168.188.1
on the new browser.



4

Enter the default password: **admin**



5

Scan and select your host router SSID

Different Channels working
together would interfere signal,
and the network speed will get
slow. Please change the
main router channel in time.




6

Enter the password of your host router


*NOTE:

Pls make sure of the right
password (special characters
not allowed, like "%")



7

Set your Extender SSID and password



8

Check again and confirm the wireless Info

*NOTE:
After check,
click "Start Connect"
and wait 30-60s



9

Wait for the repeater to connect to the router
successfully.


After the setting is completed, please observe the signal indicator. If it lights up, it means that the relay is successful. Please connect AirLive-2.4-pro to the Internet! otherwise reconnect.

Please wait 47 seconds

10

The led light "Extender" will light up, that
means it Extender Mode successfully.

*NOTE:



11

Reselect and reconnect to your extender wifi




Reconnect the extender SSID,
then get access to Internet

AP mode


If you need AP mode, please do RESET
then follow STEP 1 to STEP 4

Click [AP Settings]



Set Wireless Password

Click [Auth Mode] ---- select the encryption method,
generally select [WPA2PSK/WPA2PSK/AES]
to finish wireless password setting. Click [Apply]



Plug the Ethernet cable to the LAN port
directly then you can access the internet.

