



SP-101-US



SP-101-JP



SP-101-UK



SP-101-FR



SP-101-DE

SP-101 *Smart Plug (JP) Z-Wave Plus*

- Z-Wave Plus
- Up to 1500W resistive load
- Overload protection
- With On/Off Control scheduling and power consumption monitoring
- Act as Z-wave repeater automatically
- Longer Z-wave signal transmission
- AES 128 bit Z-wave encryption



Wake up your home equipments

Control you light or AC powered device via Z-Wave and monitor power usage. The AirLive Smart Plug SP-101 is designed to control almost any electric devices which need to be plugged into a wall socket. It can support a resistive load of up to 1500W*2 (EU) or 1500W (US/JPN) that is suitable for most of home electric equipment. When a device is plugged into the Smart Plug it can be powered on and off used the AirLive SmartLife Plus app and at the same time measure power usage for green saving.

Specifications

Model	SP-101 Smart Plug (JP) Z-Wave Plus
Z-Wave Standard	Z-wave plus
Z-Wave Frequency	JPN : 922.5Mhz
Maximum transmission distance	40 M (Indoor)
Power input Range	14.5 A
Supply Voltage	100 ~ 240 V
Maximum Output Current	15 A (Resistive Load)
Maximum Output Power	100 Vac: 1500 W
Maximum Measurement Error	3 W
LED Indicator On/Off, Include	Green / Blue
LED Indicator Power Usage	Cyan / Orange / Red

Dimension and Environment

Dimensions	58(L) x 58(W) x 37.4(H) mm
Operating Temperature	0 ~ 40° C
Storage Temperature	85% RH max

Ordering Information

Model	SP-101 Smart Plug (JP) Z-Wave Plus
-------	------------------------------------

Standard Package

Package Size	6 * 9.2 * 9.8 cm
Product Weight	
Package Weight	
Package Content	SP-101 (JP) * 1